

滤波器插入损耗表

特性 代码	电 路	标称电容		3dB 截止 频率 MHz	工作 电压 VDC	按 MIL-STD-220 (无负载) 50 Ω 系统, 最小插入损耗							
		电容值 pF	公差			5 MHz	10 MHz	20 MHz	50 MHz	100 MHz	200 MHz	500 MHz	1 GHz
A	C	68	$\pm 20\%$	77	100	-	-	-	-	-	3	10	16
B		100	$\pm 20\%$	53	100	-	-	-	-	1	6	14	19
C		135	+100/-0%	23	100	-	-	-	1	5	10	16	20
D		470	$\pm 20\%$	11	100	-	-	2	7	13	19	25	27
E		820	$\pm 20\%$	6	100	-	2	6	12	18	24	30	33
F		1000	$\pm 20\%$	5	100	-	3	7	14	20	26	32	35
G		1500	$\pm 20\%$	3.5	100	1	4	10	16	22	29	36	37
H		2500	+100/-0%	1.3	100	5	11	21	27	34	38	42	46
I		4000	+100/-0%	0.8	100	9	15	21	27	34	38	42	46
J		10	最大	635	100	-	-	-	-	-	-	-	-
L	π	680	$\pm 20\%$	65	100	-	-	-	-	1	6	17	23
M		100	$\pm 20\%$	46	100	-	-	-	-	2	9	22	28
N		135	+100/-0%	25	100	-	-	-	1	6	17	26	34
O		470	$\pm 20\%$	11	100	-	-	-	9	18	22	36	43
P		820	$\pm 20\%$	6	100	-	-	4	13	23	31	45	59
Q		1000	$\pm 20\%$	5	100	-	2	7	16	24	36	51	59
R		1700	+100/-0%	1.9	100	1	6	14	28	35	49	64	69
S		2500	+100/-0%	1.3	100	4	9	10	28	41	54	70	70
T		5000	+100/-0%	0.7	100	9	15	28	41	53	66	70	71

品质标准: MIL-F-15733

工作温度: -55 $^{\circ}$ C $\sim$ +125 $^{\circ}$ C

地址: 北京市海淀区阜成路 14 号 3 号楼 218 室 (100037)

TEL: +86-10-68371075/68371012 /68371747/68371561 FAX: +86-10- 68768863

网址: www.reintech.cn E-mail: reintech@163.com